



PREMIUM

CZUJNIKI RUCHU/MOTION DETECTORS

CZUJNIK RUCHU ZHAGA HD06VCRH7C

/ ZHAGA MOTION SENSOR HD06VCRH7C



- detektor ruchu PIR programowalny wyłącznie za pomocą pilota HD05R (brak w zestawie),
- możliwość programowania wielu czujników z jednego pilota,
- kompatybilny z gniazdem Zhaga Book 18 - dedykowany do opraw LED ANICA,
- max wysokość montażu: 12m,
- kąt/zasięg detekcji: 120 stopni/max 4m,
- czułość detekcji: 100%, 75%, 50%, 25%,
- czas utrzymania pracy czujnika: 5s, 30s, 1min, 3min, 5min, 10min, 20min, 30min,
- moc w trybie czuwania – 10%, 20%, 30%, 50%,
- długość trwania trybu czuwania – 0s, 10s, 30s, 1min, 5min, 10min, 30min, 60min, nieograniczony.

- PIR motion sensor programmable only by a remote (not included),
- one remote can program many sensors,
- compatible with Zhaga Book 18 socket – dedicated to LED ANICA fixtures,
- max. installation height: 12m,
- angle/range of detection: 120 degrees/max. 4m,
- detection sensitivity: 100%, 75%, 50%, 25%,
- sensor operation time: 5s, 30s, 1min, 3min, 5min, 10min, 20min, 30min,
- standby mode power - 10%, 20%, 30%, 50%,
- standby mode working time: 0s, 10s, 30s, 1min, 5min, 10min, 30min, 60min, unlimited.

MODEL	INDEKS	KOLOR	WYMIARY [mm]	WAGA NETTO [kg]	PAKOWANIE [szt.]	KOD EAN
MODEL	INDEX	COLOR	SIZE [mm]	NET WEIGHT [kg]	PACKING [pcs.]	BARCODE
CZUJNIK RUCHU ZHAGA HD06VCRH7C	KVLXZH	BIAŁY WHITE	Ø 47,9 x 43,1	0,03	1	5902201375985

